

## **Nexa LP 2+1 Switch**

**Power input:** 240V AC, 50/60Hz.

**Dimmer Levels:** 0 to 4

**Maximum Supportive Load** – 7.5KW (32A).

**Incandescent lamp/Resistive Load Per Channel:**1800W

**LED Load:**200 W or 6 Nos(whichever is higher)

**Inductive Load:**800W

**Typical standby power:** <0.8W.

**Operating distance from Wi-Fi router:** upto 30 meters\*. (depending upon router and its placement).

**No of Channels:** 3 (2+1)

**No. of Relay Channels:** 2

**Capacitive Dimming Channels:** 1

**Dimensions:** 103x52x16mm

**Communication Wi-Fi:** Connects to 2.4 GHz, Wi-Fi 802.11 b/g/n

**Surge Protection :** 2.5KV(Tested Upto 4KV)

**Inbuilt Fuse for extra safety**

**3-Stage Filter Circuit for Noise Suppression for Improving Endurance in Noisy Environment.**

DISCLAIMER: Do not connect multiple fans to same dimming channel\*